



BALLAST COMPATIBILITY LIST T8 PREM LED TUBE 120-277V PREM-12W-4FT-XXXK, TGL-14W-3FT-XXXK, TGL-9W-2FT-XXXK

BRAND	MODEL NUMBERS	NUMBER OF LAMPS	INPUT VOLTAGE	DIMMING
General Electric	GE132MAX-L/Ultra	1	120-277V, 347V	N
General Electric	GE232MAX-L/Ultra	2	120-277V, 347V	N
General Electric	GE332MAX-L/Ultra	3	120-277V, 347V	N
General Electric	GE432MAX-L/Ultra	4	120-277V, 347V	N
General Electric	GE232MAX-N/Ultra	2	120-277V, 347V	N
General Electric	GE332MAX-N/Ultra	3	120-277V, 347V	N
General Electric	GE432MAX-N/Ultra	4	120-277V, 347V	N
General Electric	GE232MAX-N+	2	120-277V, 347V	N
General Electric	GE432MAX-N+	4	120-277V, 347V	N
General Electric	GE132MAX-H/Ultra	1	120-277V, 347V	N
General Electric	GE232MAX-H/Ultra	2	120-277V, 347V	Y
General Electric	GE332MAX-H/Ultra	3	120-277V, 347V	N
General Electric	GE432MAX-H/Ultra	4	120-277V, 347V	N
Universal (ULT)	B132IUNVEL-N	1	120-277V, 347V	N
Universal (ULT)	B232IUNVEL-N	2	120-277V, 347V	N
Universal (ULT)	B232IUNVHE-N	2	120-277V, 347V	N
Universal (ULT)	B232IUNVHP-A	2	120-277V, 347V	N
Universal (ULT)	B332IUNVHP-A	3	120-277V, 347V	N
Universal (ULT)	B232IUNVHP-B	2	120-277V, 347V	N
Philips	ICN-3P32-N	3	120-277V, 347V	N
Philips	ICN-4P32-N	4	120-277V, 347V	N
Philips	IOP-1PSP32-N	1	120-277V, 347V	N
Philips	IOP-2PSP32-N	2	120-277V, 347V	N
Philips	IOP-2PSP32-SC	2	120-277V, 347V	N
Philips	IOP-4S32-LW-SC	4	120-277V, 347V	N
Osram	QTP1X32T8/UNV ISH-SC	1	120-277V, 347V	N
Osram	QTP2X32T8/UNV ISH-SC	2	120-277V, 347V	N
Osram	QTP3X32T8/UNV ISH-SC	3	120-277V, 347V	N
Osram	QTP1X32T8/UNV ISN-SC	1	120-277V, 347V	N
Osram	QTP2X32T8/UNV ISN-SC	2	120-277V, 347V	N
Osram	QTP3X32T8/UNV ISN-SC	3	120-277V, 347V	N
Osram	QTP4X32T8/UNV ISN-SC	4	120-277V, 347V	N
Osram	QTP1X32T8/UNV ISL-SC	1	120-277V, 347V	N
Osram	QTP2X32T8/UNV ISL-SC	2	120-277V, 347V	N
Osram	QTP3X32T8/UNV ISL-SC	3	120-277V, 347V	N
Osram	QTP4X32T8/UNV ISL-SC	4	120-277V, 347V	N

This ballast list is provided for guidance when selecting a ballast and lamp combination. Lamps were tested for compatibility with the above listed. Any ballasts which do not appear on the chart may be compatible but have not been tested.